

10 BANDE - 400 CANALI + CANALI ALFA

Canale	A		B		C		D		E		F		G		H		I	
	3° negativa	2° negativa	1° negativa	CB	1° positiva	2° positiva	3° positiva	4° positiva	5° positiva	6° positiva	3° positiva	4° positiva	5° positiva	6° positiva	3° positiva	4° positiva	5° positiva	6° positiva
1	25.615	26.065	26.515	26.965	27.415	27.865	28.315	28.765	29.215	29.665								
2	25.625	26.075	26.525	26.975	27.425	27.875	28.325	28.775	29.225	29.675								
3	25.635	26.085	26.535	26.985	27.435	27.885	28.335	28.785	29.235	29.685								
3 @lfa	25.645	26.095	26.545	26.995	27.445	27.895	28.345	28.795	29.245	29.695								
4	25.655	26.105	26.555	27.005	27.455	27.905	28.355	28.805	29.255	29.705								
5	25.665	26.115	26.565	27.015	27.465	27.915	28.365	28.815	29.265	29.715								
6	25.675	26.125	26.575	27.025	27.475	27.925	28.375	28.825	29.275	29.725								
7	25.685	26.135	26.585	27.035	27.485	27.935	28.385	28.835	29.285	29.735								
7 @lfa	25.695	26.145	26.595	27.045	27.495	27.945	28.395	28.845	29.295	29.745								
8	25.705	26.155	26.605	27.055	27.505	27.955	28.405	28.855	29.305	29.755								
9	25.715	26.165	26.615	27.065	27.515	27.965	28.415	28.865	29.315	29.765								
10	25.725	26.175	26.625	27.075	27.525	27.975	28.425	28.875	29.325	29.775								
11	25.735	26.185	26.635	27.085	27.535	27.985	28.435	28.885	29.335	29.785								
11 @	25.745	26.195	26.645	27.095	27.545	27.995	28.445	28.895	29.345	29.795								
12	25.755	26.205	26.655	27.105	27.555	28.005	28.455	28.905	29.355	29.805								
13	25.765	26.215	26.665	27.115	27.565	28.015	28.465	28.915	29.365	29.815								
14	25.775	26.225	26.675	27.125	27.575	28.025	28.475	28.925	29.375	29.825								
15	25.785	26.235	26.685	27.135	27.585	28.035	28.485	28.935	29.385	29.835								
15 @	25.795	26.245	26.695	27.145	27.595	28.045	28.495	28.945	29.395	29.845								
16	25.805	26.255	26.705	27.155	27.605	28.055	28.505	28.955	29.405	29.855								
17	25.815	26.265	26.715	27.165	27.615	28.065	28.515	28.965	29.415	29.865								
18	25.825	26.275	26.725	27.175	27.625	28.075	28.525	28.975	29.425	29.875								
19	25.835	26.285	26.735	27.185	27.635	28.085	28.535	28.985	29.435	29.885								
19 @	25.845	26.295	26.745	27.195	27.645	28.095	28.545	28.995	29.445	29.895								
20	25.855	26.305	26.755	27.205	27.655	28.105	28.555	29.005	29.455	29.905								
21	25.865	26.315	26.765	27.215	27.665	28.115	28.565	29.015	29.465	29.915								
22	25.875	26.325	26.775	27.225	27.675	28.125	28.575	29.025	29.475	29.925								
23	25.905	26.355	26.805	27.255	27.705	28.155	28.605	29.055	29.505	29.955								
24	25.885	26.335	26.785	27.235	27.685	28.135	28.585	29.035	29.485	29.935								
25	25.895	26.345	26.795	27.245	27.695	28.145	28.595	29.045	29.495	29.945								
26	25.915	26.365	26.815	27.265	27.715	28.165	28.615	29.065	29.515	29.965								
27	25.925	26.375	26.825	27.275	27.725	28.175	28.625	29.075	29.525	29.975								
28	25.935	26.385	26.835	27.285	27.735	28.185	28.635	29.085	29.535	29.985								
29	25.945	26.395	26.845	27.295	27.745	28.195	28.645	29.095	29.545	29.995								
30	25.955	26.405	26.855	27.305	27.755	28.205	28.655	29.105	29.555	30.005								
31	25.965	26.415	26.865	27.315	27.765	28.215	28.665	29.115	29.565	30.015								
32	25.975	26.425	26.875	27.325	27.775	28.225	28.675	29.125	29.575	30.025								
33	25.985	26.435	26.885	27.335	27.785	28.235	28.685	29.135	29.585	30.035								
34	25.995	26.445	26.895	27.345	27.795	28.245	28.695	29.145	29.595	30.045								
35	26.005	26.455	26.905	27.355	27.805	28.255	28.705	29.155	29.605	30.055								
36	26.015	26.465	26.915	27.365	27.815	28.265	28.715	29.165	29.615	30.065								
37	26.025	26.475	26.925	27.375	27.825	28.275	28.725	29.175	29.625	30.075								
38	26.035	26.485	26.935	27.385	27.835	28.285	28.735	29.185	29.635	30.085								
39	26.045	26.495	26.945	27.395	27.845	28.295	28.745	29.195	29.645	30.095								
40	26.055	26.505	26.955	27.405	27.855	28.305	28.755	29.205	29.655	30.105								

- Da 28 Mhz a 29,7Mhz Banda radioamatoriale - da 28Mhz a 28,190 CW esclusivo
- 27,555 Mhz Canale 12 di chiamata internazionale per DX in USB
- 27,615 Mhz Canale 17 monitor ROGERKAPPA DX GROUP in USB